


NM CABLE FITTINGS & SUPPORTS

PLASTIC PUSH-IN CONNECTORS

For NM and flexible cord.



CATALOG NUMBER	UPC/DCI/NAED MFG #01 8997	TRADE SIZE	K.O. SIZE	UNIT PKG	STD PKG	DIM A	DIM B	DIM C
NM840	54840	3/8	1/2	100	1000	1.031	.375	.965
NM841	54841	1/2	1/2	50	500	1.340	.475	1.125
NM842	54842	3/4	3/4	25	250	1.510	.475	1.200
NM843	54843	1	1	25	250	1.637	.475	1.500
NM844	50175	1-1/4	1-1/4	10	100	2.085	.475	2.012




[Click here](#) for complete cable ranges.



E28474 LR49636

INSTALLATION INSTRUCTIONS


1. Push the connector into knock out.
2. Install required cables or cords.
3. Place wedge in connector slot and lock tight with a pair of pliers. Tightened wedge provides strong, positive grip.



1



2



3

[Products Index](#)

[Table of Contents](#)

[Next](#)



Arlington Industries, Inc.

800-233-4717 | FAX 570-562-0646 | 1 STAUFFER INDUSTRIAL PARK. SCRANTON, PA 18517
[CONTACT US](#) Copyright © 2000 All rights reserved. Revised: October 07, 2003.