



Motor-Protective Circuit-Breakers, 6, 3-10 A, 3 p

Part no. **Z-MS-10/3**
 Catalog No. **248411**
 Eaton Catalog No. **Z-MS-10/3**

Similar to illustration

Technical data ETIM 6.0

Low-voltage industrial components (EG000017) / Motor protection circuit-breaker (EC000074)			
Electric engineering, automation, process control engineering / Low-voltage switch technology / Circuit breaker (LV < 1 kV) / Motor protection circuit-breaker (ecl@ss8.1-27-37-04-01 [AGZ529013])			
Overload release current setting	A		6.3 - 10
Adjustment range undelayed short-circuit release	A		78 - 105
Thermal protection			Yes
Phase failure sensitive			No
Switch off technique			Magnetic
Rated operating voltage	V		400 - 400
Rated permanent current I _u	A		10
Rated operation power at AC-3, 230 V	kW		0
Rated operation power at AC-3, 400 V	kW		4
Type of electrical connection of main circuit			Screw connection
Type of control element			Rocker lever
Device construction			Complete device in housing
With integrated auxiliary switch			No
With integrated under voltage release			No
Number of poles			3
Rated short-circuit breaking capacity I _{cu} at 400 V, AC	kA		0
Degree of protection (IP)			IP20
Height	mm		75
Width	mm		54
Depth	mm		80