

SPECIFICATION & FEATURES

4" Square Box Cut-In Adapter

DESCRIPTION:

Orbit Industries' Universal Cut-In Adapters, UCIA-4S and FA-UCIA-4S, enable any 4" square junction box to be used in old work applications. Installers can quickly mount 4" sq. boxes of any depth into existing walls. Includes two (2) old work clips that firmly secure boxes to finished drywall or plaster, without risk of pull-out. Small footprint is easily covered by large appliances and devices. FA-UCIA-4S is powder coated red for quick identification of FA devices.



UCIA-4S

FA-UCIA-4S

FEATURES:

- Old work steel clips secure 4" square boxes of any depth into existing walls
- Accommodates 4" square steel junction boxes of any depth
- Two (2) integrated old work steel clips with screws for 3/8" to 1-1/2" drywall or other wall materials
- Small footprint easily concealed by life safety devices greater than 4-13/32" W x 4-3/4" H
- See **Wall Mounting Template** in next page, it can be printed for easy tracing and cut-out
- Zinc Plated Steel

CONFIGURATION DATA:

Suggested Box Pairing:

- 4SDB-MKO: 4" Sq., 2-1/8" Deep Box with 1/2" & 3/4" MKO's
- FA-4SDB-MKO: Red 4" Sq., 2-1/8" Deep Box with 1/2" & 3/4" MKO's
- FA-4SDB-75: Red 4" Sq., 2-1/8" Deep Box with 3/4" KO's
- 4SEDB-CKO: 4" Sq., 3-1/2" Deep Box with 1/2" & 3/4" CKO's
- FA-4SEDB-CKO: Red 4" Sq., 3-1/2" Deep Box with 1/2" & 3/4" CKO's

Cat. No.	Description	Std.Pkg.
UCIA-4S	Cut-In Adapter for 4S Box	20
FA-UCIA-4S	Red Cut-In Adapter for 4S Box	20



UCIA-4S Installed



FA-UCIA-4S Installed



ATTENTION:

**TO USE TEMPLATE FOR INSTALLATION,
DIMENSIONS MUST BE AS SHOWN $\pm 1/16"$ [1.58mm]
AFTER PRINTING (SHEET SIZE 8.5 X 11)**

Installation Template:

